



- Super-IPS panel with 170° Horizontal and Vertical viewing angles
- Theft resistant wall mounting bracket included
- Built-In Pillow Speaker Interface with analog, digital and digital direct access control
- Enhanced Pillow Speaker Function- Allows power on/off and the TV A/V switch to be accessed through the pillow speaker
-  and  Certified for Healthcare Use (6500)
- Energy Star qualified product
- OSHA and OSHPD exempt mounting configurations



## PDi P23LCD 23" LCD Television

PDI Communication Systems  
 40 Greenwood Lane  
 Springboro, Ohio 45066  
 p. 937 743-6010/1 800 628-9870  
 f. 937 743-5664  
[www.pdiarm.com](http://www.pdiarm.com)



# Inova<sup>23</sup>

# Inova<sup>23</sup>

- 16 by 9 wide screen Aspect Ratio
- 1366 by 768 Resolution
- Color Depth 16.7M True Color
- 800:1 Contrast Ratio
- 500 cd/m<sup>2</sup> brightness
- 50K Hours Lamp Life
- Closed Captioning
- 1/4" Phono Input for Pillow Speaker
- 100mm VESA Mounting Pattern
- V-Chip with ability to Set on to activate V-Chip (Parental Control)
- *Start Channel* — When active, this function allows the user to determine the initial channel when the TV is turned ON
- *Start Volume* — This function allows the user to determine the initial volume level setting when the TV is turned ON

PDI

- *Minimum Volume* — This function determines the minimum volume level allowable with the Volume Up/Down control.
- *Maximum Volume* — This function determines the maximum volume level allowable with the Volume Up/Down control.
- *Channel Lock* — Anytime the television is powered on the TV will always be on the same channel. Channel Up/Down will have no control over the television.
- *Lock-out* — When turned on the Menu and A/V switch on the front of the set are disabled.
- *Channel Override* — When set to off position, the user can select channels with either Channel Up/Down or by direct keypad entry. When set to on position, only those channels that are entered for scanning may be selected by direct keypad entry.
- *Caption Lock* — When function is on, previous Closed Caption On/Off state is restored after TV turns off. When function is off, the captions are always off when TV is initially turned on.
- *Four Programmable Memory Banks* — Each memory bank can include up to 125 channels in CATV mode. Memory banks 1–3 can be independently programmed and have the ability to copy and clear any memory bank. Bank 4 is used to lock the TV in the “off” state.
- *Clone Programmer* — Program one TV with all settings then transfer the settings to every similar set in the system.
- *Bed A and Bed B IR Remote Settings* — Allows two televisions to be in the same room without the IR signals interfering with one another.
- *Auto Power ON* — When set to on position, television powers up any time power is applied. When set to off position, television functions normally.
- *Auto Programming* — Automatically programs TV to available channels and selects tuning band that is available.
- *Power Management* — Allows the flexibility to automatically power off the television after a specific period of inactivity.
- “CCI” Interface port for computer control interface.
- Complete unit (including Television, Power supply brick and Power Cord weighs less than 18 pounds 10 ounces (8.448 KG).
- RGB Connector for VGA monitor capability.
- Ceiling, table and optional wall mounting solutions available.

